

AVANT GUARD

SMART HOME

MODEL H11 Smart Lock

Complete User Settings Guide

HOW TO ENTER SETTINGS MODE

Press * # and verify admin info. First time setting: default Admin password is **123456#**. Press * # then enter 123456# to add the first admin.

MAIN MENU

KEY	FUNCTION	DESCRIPTION
1	Admin Setting	Add Admin, Delete Admin (by ID), Network Setting
2	User Setting	Add User, Delete User By ID
3	System Setting	Volume, Unlock Mode, Language, Time Setting, Room Number
4	Setting Initialization	Factory reset the lock

1 ADMIN SETTING

OPTION	DESCRIPTION
1 Add Admin	Register a new administrator credential (Fingerprint x5 / Password 6-8 digits / Card)
2 Delete Admin (Delete By ID)	Enter the admin ID number to delete that administrator
3 Network Setting	Configure WiFi/network connectivity for the lock

2 USER SETTING

OPTION	DESCRIPTION
1 Add User	

	Register a new regular user (Fingerprint x5 / Password 6-8 digits / Card)
2 Delete User By ID	Enter the user ID number to remove that user's access

3 SYSTEM SETTING

1 Volume Setting

OPTION	DESCRIPTION
1 Turn On	Enable speaker sounds and voice prompts
2 Turn Off	Mute all sounds (silent mode)

2 Unlock Mode

OPTION	DESCRIPTION
1 Single Unlock	One credential sufficient to open the door
2 Combination Unlock	Two credentials required to open (dual authentication)

3 Language Setting

OPTION	LANGUAGE
1 Chinese	Chinese (Mandarin)
2 English	English
3 Russian	Russian
4 Vietnam	Vietnamese
5 Indonesia	Indonesian

4 Time Setting

Enter current date and time: YYYY / MM / DD format.

5 Room Number

Can be ignored if not applicable to your setup.

4 SETTING INITIALIZATION

Resets the lock to factory defaults — all users and settings are erased.

CREDENTIAL NOTES

Fingerprint: Scan 5 times for complete registration.

Password: Enter 6-8 digit PIN.

First time: Press * # → enter 123456# → this is the default first admin password.

QUICK TIPS

Credentials supported: Fingerprint, Password (6-8 digits), IC Card.

Combination Unlock: Requires two different credentials — ideal for high-security environments.

5 languages supported: Chinese, English, Russian, Vietnamese, Indonesian.

Network Setting: Access via Admin Setting option 3 to connect lock to WiFi/app.