

AVANT GUARD

SMART HOME

P22 Smart Lock

Complete User Settings Guide

SETTINGS ENTRY

STEP 1 * <i>Press * to wake the lock</i>	STEP 2 # <i>Press # to enter Admin mode</i>	STEP 3 Verify <i>Verify admin info (fingerprint / card / 6–8 digit password). Default password: 123456</i>
---	--	--

MAIN MENU

#	Menu Item	Description
1	Admin Setting	Manage administrator accounts
2	User Setting	Manage regular user accounts
3	Datetime Setting	Set date and time
4	System Setting	Configure lock behavior and functions
5	Other Setting	Restore, unlock records, system info

1. ADMIN SETTING

Sub-Menu	Action / Value
Add Admin	Enter ID 001–010 → Scan fingerprint / card / enter 6–8 digit password
Delete Admin	Enter ID to delete
Add Face	Enroll face to register

2. USER SETTING

Sub-Menu	Action / Value
Add User	Enter ID 01–099
Delete User	Enter ID to delete (01–099)
Add Face	Enroll face (right/left/up/down/up)

3. DATETIME SETTING

Field	Format
Date	Year / Month / Day
Time	Hour / Minute

4. SYSTEM SETTING

Navigate with **Press # to Next, Press * to Back**

Sub-Menu	Option	Values
Function Setting > Language Setting	Language	Chinese / English
	Door Direction	Left / Right
Function Setting > Door Function	Auto Lock	0sec – 10sec / Off
	Latch Back Time	0sec – 15sec
	Torque Set	Min / Med / Max
	Pop Tongue	2 / 5 / 4 / 6
	Back Tongue	2 / 5 / 4 / 6
	Rotation Time	1sec – 9sec
	Auto Popup	On / Off
Function Setting > Verify Mode	Single Mode	—
	Combine Mode / Composite	—
	Volume Setting	Volume + / Volume – / Mute
Network Setting	Distance	Off / Mid / Near / Far
	Tamper Alarm	On / Off
	Face Mute	On / Off

	Network Match	Connecting
Network Setting > Unbind Network	Unbind	Delete

5. OTHER SETTING

Sub-Menu	Description
Restore	Press * to back, Press # to confirm factory reset
Unlock Records	View unlock history logs
Admin Info	View registered admin accounts
User Info	View registered user accounts
Version	View firmware version

NOTES & TIPS

Fingerprint Registration: Scan 5 times for best accuracy.

Password Registration: 6–8 digits required.

First Time Setup: Default admin password is **123456**.

To Enter Admin: Press * then # then verify admin info. At initialization state, default password is 123456#.

Authentication Methods: Fingerprint, Face, Card (IC), PIN (6–8 digits)