

AVANT GUARD

SMART HOME

P32 0924 Smart Lock

Complete User Settings Guide

SETTINGS ENTRY

STEP 1	STEP 2	NOTES
*# <i>Press *# to Verify Admin (in initialize state)</i>	Password <i>Enter Admin Password. Default: 123456#</i>	— <i>Fingerprint: Scan 5 times. Password: 6–8 digits. First time: Press *# then enter 123456# to add new admin.</i>

MAIN MENU

#	Menu Item	Description
1	Administrator	Manage administrator accounts (Fingerprint/Password/IC/Face)
2	User	Manage regular user accounts
3	Set Up	Network, Date/Time, Mode, Function, Volume settings
4	Information	Records, Statistics

1. ADMINISTRATOR

Sub-Menu	Method / Action	Details
Add	Fingerprint / Password / IC	Enter ID number, EX: 000, and scan fingerprint/card/enter password#
	Face	Scan face to register (Lift head up, down, turn right, turn left)
Delete	Enter ID Number	Enter ID number to delete. EX: 00#
Reset	Confirm	Press # to confirm

	Cancel	Press * to back
Sensor	High	High sensitivity
	Mid	Medium sensitivity
	Low	Low sensitivity
	Off	Sensor disabled

2. USER

Sub-Menu	Method / Action	Details
Add	Fingerprint / Password / Card	Enter ID number start from 010–199 (EX: 010), scan fingerprint/card/enter password#
	Face	Scan face to register (Lift head up, down, turn right, turn left)
Delete	Enter ID Number	Enter ID number to delete. EX: 010#

3. SET UP

Sub-Menu	Option	Values
Network	Turn On / Turn Off	Enable or disable network connectivity
Date Time Setting	Date & Time	Enter Your Current Time (Year : Month : Date / Hour : Minute)
Mode	Single Mode	Single authentication required
	Double Mode	Dual authentication required
	Lock Back Time	2–9 seconds
Function Setting	Auto Lock	5 / 10 / 15 / 20 / 25 / 30 / 35 / 40 second or OFF
	Alarm	On / Off
	Card	On / Off
	System Volume	00–06 levels
Volume	Bell Volume	00–06 levels

4. INFORMATION

Sub-Menu	Option	Details
----------	--------	---------

Records	5 to Forward	View next 5 records
	8 to Back	View previous 8 records
Statistics	Administrators	Count of registered administrators
	User	Count of registered users

AUTHENTICATION METHODS

Method	Details
Fingerprint	Scan 5 times for accurate registration
Face	Lift head up, down, turn right, turn left
Password (PIN)	6–8 digit numeric code, end with #
IC Card	Scan RFID/IC card at reader

NOTES & TIPS

Default Admin Password: 123456#

Admin ID Range: 000 and above

User ID Range: 010–199

Auto Lock Options: 5, 10, 15, 20, 25, 30, 35, 40 seconds or OFF

Volume: System volume and bell volume configurable from 00 to 06