

AVANT GUARD

SMART HOME

MODEL OF11 Smart Lock

Complete User Settings Guide

HOW TO ENTER SETTINGS MODE

Touch to wake the screen, then press # and enter administrative verification.

Security Note: In factory state any fingerprint can unlock the door. Add an administrator password and fingerprint immediately to secure the lock.

MAIN MENU

MENU	FUNCTION
1 User Management	Add Users, Delete User, Clear User, Record Query
2 System Settings	Set parameters, Adjust volume, Switch wireless device, Adjust time
3 Chinese-English Switching	Change display/voice language

1 USER MANAGEMENT

1 Add Users

USER TYPE	CREDENTIALS
1 Add an administrative user	Enter password (6-14 digits, press # to end after entry), fingerprint, card, or wireless device
2 Add a normal user	Enter password, fingerprint, card, or wireless device

2 Delete User

Enter password, fingerprint, card, wireless device, or its ID number to identify and delete the user.

3 Clear User

Enter administrator verification to clear all users from the lock.

4 Record Query

Input # to turn backwards through records, input * to turn forward through access history.

2 SYSTEM SETTINGS

1 Set Parameters

OPTION	VALUES
Set the lock mode	1 Automatic lock / 2 Manual lock
Set the unlocking hold time	Enter hold time in seconds (00-99)

2 Adjust the Volume

OPTION	ACTION
1 Increase the volume	Raise speaker volume one level
2 Decrease the volume	Lower speaker volume one level

3 Switch Wireless Device

OPTION	NOTE
Turn on wireless device	Enable remote/wireless functionality
Turn off wireless device	Remote control cannot be used when off

4 Adjust Time

Set current date and time on the lock.

3 LANGUAGE SWITCHING

OPTION	LANGUAGE
1 Chinese	Voice prompts in Chinese (Mandarin)
2 English	Voice prompts in English

QUICK TIPS

Credentials supported: Password (6-14 digits), Fingerprint, IC Card, Wireless device.

Long password support: OF11 supports passwords up to 14 digits — longer passwords offer more security.

Unlock hold time: 00-99 seconds — how long the latch stays retracted after unlocking.

Record Query: Press # to go backwards through history, * to go forward — review all access events.