

AVANT GUARD

SMART HOME

MODEL P20 Smart Lock

Complete User Settings Guide

HOW TO ENTER SETTINGS MODE

Press * # + **Admin Password** to enter Admin Setting, then select **1 Local Setting**.

MAIN MENU

MENU	FUNCTION
Admin Setting > 1 Local Setting	Add User, Delete User, Options (Function/Volume/Language/ More Settings), Add Admin
WiFi Setting	Press * # + Admin Password > App Setting: Add Module / Delete Module
Lock Install	Press * # + Admin Password > Install: Motor, Rotation Time, Set Close Time, Autolock
Factory Reset	Insert pin into reset button, press and HOLD 8 seconds, press # to confirm

ADD USER

CREDENTIAL	STEPS
Fingerprint	Scan Fingerprint 4 times
Password	Enter Password + # (repeat 2 times)
Card	Scan card on reader

DELETE USER

Enter ID to delete + #

OPTIONS MENU

SUB-MENU	OPTION	VALUES
1 Function Settings	Enable / Disable Dual Verify	Two credentials required
	Enable / Disable Alarm	Anti-tamper alarm
	Enable / Disable Mute	Silent operation
2 Volume Settings	Volume Up	Increase speaker volume
	Volume Down	Decrease speaker volume
3 Language Settings	Chinese	Chinese Mandarin prompts
	English	English prompts
4 More Settings	Time Setting	Set current date and time
	Record	View access history log
	Initialize	Factory reset lock

ADD ADMIN

CREDENTIAL	STEPS
Fingerprint	Scan Fingerprint 4 times
Password	Enter Password + # (repeat 2 times)
Card	Scan card on reader

WIFI / APP SETTING

OPTION	ACTION
Add Module	Pair new WiFi module — Add Device on Smartlife App
Delete Module	Remove existing WiFi module

LOCK INSTALL

OPTION	VALUES
Motor	1 Left / 2 Right
Rotation Time	Press 1
Set Close Time	Press 9
Autolock	Enable / Disable

QUICK TIPS

Credentials supported: Fingerprint (4 scans), Password, IC Card.

Dual Verify: Requires two different credentials to open the door.

Motor direction: Set Left or Right under Lock Install to match your door configuration.

WiFi: Access App Setting via Admin menu to add/remove the wireless module for Smartlife App control.