

AVANT GUARD

SMART HOME

MODEL S10 Smart Lock

Complete User Settings Guide

HOW TO ENTER SETTINGS MODE

Press * # + **Admin Password** to enter Admin Setting mode.

MAIN MENU

MENU	FUNCTION
Admin Setting	Add User, Delete User, Lock Setting, Add Admin
Lock Reset	Open back cover, press and HOLD 6 seconds on reset button
WiFi Setting	Open back cover, press ONCE on reset button — Add Device on Smartlife App
WiFi Change	Master Reset — WiFi Setting (First Time)

ADD USER

CREDENTIAL	STEPS
Fingerprint	Scan fingerprint to enroll
Card	Scan IC card on the reader
Password	Enter Password + #

DELETE USER

METHOD	STEPS
Fingerprint	Scan fingerprint to delete
Card	Scan card to delete

Password	Enter Password to delete + #
By ID	Enter ID to delete + #

LOCK SETTING

1 Function Settings

OPTION	VALUES
Enable / Disable Passage Mode	Door stays unlocked in passage mode
Enable / Disable Dual Verify	Two credentials required to unlock
Enable / Disable Anti Burglar Alarm	Tamper/intrusion alarm on/off
Enable / Disable Mute	Silent operation on/off

2 Volume Settings

OPTION	ACTION
Volume Up	Increase speaker volume
Volume Down	Decrease speaker volume

3 Language Settings

OPTION	LANGUAGE
Chinese	Chinese (Mandarin) voice prompts
English	English voice prompts

4 Time Setting

Enter New Date and Time to sync the lock clock.

ADD ADMIN

CREDENTIAL	STEPS
Fingerprint	Scan fingerprint to register admin
Card	Scan card to register admin
Password	Enter Password + # to register admin

HARDWARE RESET & WIFI

ACTION	HOW TO	RESULT
Lock Reset	Open back cover, press and HOLD 6 seconds on reset button	Factory reset — all data cleared
WiFi Setting	Open back cover, press ONCE on reset button	Add Device on Smartlife App
WiFi Change	Master Reset	WiFi Setting (First Time) — reconfigure network

QUICK TIPS

Credentials supported: Fingerprint, IC Card, Password.

Passage Mode: Enable for open-door periods — door stays unlocked until you disable passage mode.

Dual Verify: Two credentials required — heightened security for sensitive areas.

WiFi — press once (not hold): Single press enters WiFi pairing mode for Smartlife App. Hold 6s resets the lock completely.